

Instructions on Updating Firmware on Picture Porter -

Firmware version: F7-1.2.8

Firmware file: 'FRF7G128.MMV'

A. Copying firmware file to Picture Porter

1. Unzip the 'FRF7G128.ZIP' file and note the location of the unzipped file. This file will be named 'FRF7G128.MMV.'
2. Connect Picture Porter to your computer.
3. Copy the unzipped file 'FRF7G128.MMV' onto the Picture Porter hard drive. You can copy it to any folder location on the Picture Porter hard drive, but to make it easy to remember, we recommend putting it in the folder labeled "DATA".
4. Disconnect Picture Porter from the computer.

Note: Instead of transferring the firmware update file by USB connection, you can also copy the file to a memory card use the Copy and Paste function to copy the file from the inserted memory card to your Picture Porter hard drive.

B. Updating firmware:

1. Make sure your Picture Porter is disconnected from the computer.
2. On Picture Porter, navigate to and select the file "FRF7G128.MMV"***
3. The message 'Update Firmware?' will pop up. Click on Yes to update it.
4. Wait for 40 seconds for the firmware to update.
* DO NOT interrupt the firmware update while it is in process. Stopping the firmware update before it is completed may damage your device and make it inoperable.
5. Click ENTER/SEL to complete the update.
** CAUTION: For the same reason explained in the note of step #4 above, it is important to have your Picture Porter connected to AC power while performing the firmware update.

C. To confirm that firmware is updated:

1. Go into Options
2. Click on the MNU button twice to go to VERSION tab
3. Firmware version should say F7-1.2.8

New Features on Picture Porter Firmware V1.2.8 -

Photo viewing & format support:

- Added RAW format support for Canon 400D, Canon Digital Rebel, Sony Alpha A100 and Panasonic FZ50
- Fixed MRW color bug
- Fixed Nikon D200 thumbnail bug

Back-up function:

- Added "compare" function after "full backup" and shows disk free space.
- Fixed file copy bug when short-name is different from long-name

Video playback:

- Improved Sanyo C1 file A/V sync problem
- Enhanced volume display control while playing MPEG-4

Music playback:

- Added Jukebox Features: (1) Supports "scrolling display of TAG information" (2) Supports "scrolling display of highlighted item in playlist view" (3) Supports "Variable speed FF and FB" (4) Supports "ID3v2.2"
- Added Jukebox display "remaining time" function

Other bug fixes and feature enhancement:

- Fixed PS2002 error message when PS2002 doesn't exist or ID error
- Decreased LCD backlight while backing-up to save battery life
- Fixed bug: Jukebox could not start after playlist was cleared
- Fixed bug: Display time not showing correctly when playing videos
- Fixed bug: Computer sometimes could not recognize hard drive if connecting Picture Porter to the computer with CF card inserted